

EMERSON SELL UPS!

UP-SELL OPTIONS, READ UP-SELL QUESTIONS IN SECTION 3 FOR HELP

UPS	List ex GST	IS A RACK KIT INCLUDED	WEBCARD	MICROPOD	BATTERY PACK	1YR WARRANTY EXTENSION	Run time at 50% & 100% Load (mins)
PSA500MT3-230U	\$135	-	-	-	-	\$24	12 / 4
PSA650MT3-230U	\$167	-	-	-	-	\$30	9 / 3
PSA1000MT3-230U	\$257	-	-	-	-	\$42	12 / 4
PSA1500MT3-230U	\$333	-	-	-	-	\$42	12 / 4
PS750RT3-230	\$985	Yes	A	C	-	\$165	11 / 4
PS1000RT3-230	\$1014	Yes	A	C	-	\$180	12 / 4
PS1500RT3-230	\$1230	Yes	A	C	-	\$205	9 / 3
PS2200RT3-230	\$1528	Yes	A	D	-	\$245	11 / 3
PS3000RT3-230	\$1877	Yes	A	D	-	\$355	9 / 3
GXT4-700RT230	\$1166	Yes*	B	C	E*	\$127	27 / 11
GXT4-1000RT230	\$1278	Yes*	B	C	E*	\$273	17 / 6
GXT4-1500RT230	\$1886	Yes*	B	C	E*	\$332	18 / 6
GXT4-2000RT230	\$2441	Yes*	B	C+	E*	\$332	12 / 3
GXT4-3000RT230	\$3555	Yes*	B	D	F*	\$390	12 / 3
GXT4-5000RT230	\$5799	Yes**	Inc	Inc	G**	\$592	21 / 9
GXT4-6000RT230	\$6205	Yes**	Inc	Inc	G**	\$617	17 / 6
GXT4-10000RT230	\$7422	Yes**	Inc	Inc	G**	\$685	12 / 4

2

ACCESSORIES \$ List Ex

RMKIT18-32 (Slide rail type)	**	\$184	RMKIT (Basic Bracket type)	*	Inc
IS-WEBRT3	A	\$547	GXT4-48VBATT inc RMKIT	E	\$931
IS-WEBCARD	B	\$524	GXT4-72VBATT inc RMKIT	F	\$1265
Micropod - MP2-210K	C	\$467	GXT4-240VBATT inc RMKIT18-32	G	\$2802
Micropod - MP2-220L	D	\$524	Cable - CPC1CC180-R12	+	\$99

3

Up-sell Questions

'do you need to connect to the UPS over a network?'

YES – Add Webcard

'do you want to be able to conduct maintenance on the UPS without loosing power to the load that the unit is supporting?'

YES – Add a Micropod (also called a bypass switch)

'do you want to monitor the temperature & humidity where the UPS is located?'

YES – Add a SIC Card which includes a temp/humidity sensor.

Part: 02311646 \$717 ex GST List Price

4

Help!

I'm confused.. I just want to give someone the list of equipment I need a UPS to support & get them to quote me the right UPS with the necessary accessories!

NO PROBLEMS, SEND THE BOM TO SALES@POWERQC.COM.AU & WE'LL DO THE WORK FOR YOU. OR CALL US ON 1800 543 237

TECHNICAL GUIDE



Liebert PSA



Liebert Micropod



Liebert PSI



IS-Webcard



Liebert SIC

Liebert GXT4 700 – 3kVA



Liebert GXT4 5kVA, 6kVA & 10kVA

UPS	WATTS	POWER FACTOR (PF)	INPUT	OUTLET POINTS	TECHNOLOGY	START UP & PRODUCT CONFIGURATION	UPS RU / Balf RU	WEIGHT Kg
PSA500MT3-230U	300	0.6	10 Amp GPO	3 x 10A C13	Line Interactive	Plug & Play – Mini Tower	NA	7
PSA650MT3-230U	390	0.6	10 Amp GPO	3 x 10A C13	Line Interactive	Plug & Play – Mini Tower	NA	7.5
PSA1000MT3-230U	600	0.6	10 Amp GPO	6 x 10A C13	Line Interactive	Plug & Play – Mini Tower	NA	12
PSA1500MT3-230U	900	0.6	10 Amp GPO	6 x 10A C13	Line Interactive	Plug & Play – Mini Tower	NA	14
PS750RT3-230	675	0.9	10 Amp GPO	8 x 10A C13	Line Interactive	Plug & Play – Rack/Tower	2U	15
PS1000RT3-230	900	0.9	10 Amp GPO	8 x 10A C13	Line Interactive	Plug & Play – Rack/Tower	2U	30
PS1500RT3-230	1350	0.9	10 Amp GPO	8 x 10A C13	Line Interactive	Plug & Play – Rack/Tower	2U	32
PS2200RT3-230	1980	0.9	15 Amp GPO	8 x 10A C13 + 1 x 15A C19	Line Interactive	Plug & Play – Rack/Tower	2U	38
PS3000RT3-230	2700	0.9	15 Amp GPO	8 x 10A C13 + 1 x 15A C19	Line Interactive	Plug & Play – Rack/Tower	2U	42
GXT4-700RT-230	630	0.9	10 Amp GPO	6 x 10A C13	On-line Double Conversion	Plug & Play – Rack/Tower	2U / 2U	20.5
GXT4-1000RT-230	900	0.9	10 Amp GPO	6 x 10A C13	On-line Double Conversion	Plug & Play – Rack/Tower	2U / 2U	20.5
GXT4-1500RT-230	1350	0.9	10 Amp GPO	6 x 10A C13	On-line Double Conversion	Plug & Play – Rack/Tower	2U / 2U	23
GXT4-2000RT-230	1800	0.9	15 Amp GPO*	6 x 10A C13	On-line Double Conversion	Plug & Play – Rack/Tower	2U / 2U	25.5
GXT4-3000RT-230	2700	0.9	15 Amp GPO	6 x 10A C13 + 1 x 15A C19	On-line Double Conversion	Plug & Play – Rack/Tower	2U / 2U	34
GXT4-5000RT-230	4000	0.8	25 Amp Hard Wired by Electrician	2 x C19 (15A), + 6 x C13 (10A)	On-line Double Conversion	Electrician required, refer PQC – Rack/Tower	5U / 4U	71
GXT4-6000RT-230	4800	0.8	32 Amp Hard Wired by Electrician	2 x C19 (15A), + 6 x C13 (10A)	On-line Double Conversion	Electrician required, refer PQC – Rack/Tower	5U / 4U	71
GXT4-10000RT-230	9000	0.9	50 Amp Hard Wired by Electrician	4 x C19 (15A), + 4 x C13 (10A)	On-line Double Conversion	Electrician required, refer PQC – Rack/Tower	6U / 4U	92

IMPORTANT NOTES:

- *10 Amp with adapter cable 'CPC1NC180-R12' – List Price \$99 ex GST
- Items with Orange Part No. are NOT held in stock, extended lead times apply.
- Item shaded in Green are Plug & Play but need a 15 Amp outlet, this may require an Electrician to install.

1800 543 237

www.powerqc.com.au sales@powerqc.com.au